

# Programming DOMOTICA remote control

## 1 Receiver domotica connect to ECB control box:

Unscrew the connection cover from the ECB control box.



Connect the wiring as described below.



Blue = N (zero)  
Black = L1(phase)



Brown = 4  
Purple = 2


## 2 Receiver programming:

Push with a screwdriver once of the on / off button of the receiver and the red LED will light up.

Then push once on the left button of the remote control and the red LED flashes 2 times.

Push with a screwdriver once on the on / off button and the LED goes out.

Receiver is now programmed and ready for use.



## 3 Receiver reset:

Push with a screwdriver once on the on / off button of the receiver and the red LED will be light up.

Hold the on / off button for 5 seconds and the LED flashes 5 times.

Wait for 5 seconds until the red LED goes out.

The receiver is now reset and can be programmed again.